

W2NJR

Over-the-Air EchoIRLP Commands

| | |
|--------------------------------|-----------|
| Connect to IRLP Node xxxx | 4757xxxx |
| Connect to Echolink Node xxxxx | 3246xxxxx |
| Play Info | 3246* |
| Query by Call | 324607 |
| Query by Node | 324606 |
| Random Conf | 324602 |
| Random Link | 324601 |
| Random Node | 324600 |
| Random User | 324603 |
| Reconnect | 324609 |
| Status | 324608 |
| Disconnect | 73 |

NOTES:

- 1. The control prefix 3246 spells ECHO, and prefix 4757 spells IRLP on your touch-tone mic. If you forget the codes, think of the phrases “ECHO” and “IRLP”!***
- 2. Most repeaters normally mute the DTMF tones. In order to pass your DTMF tones “upstream” to the Echolink node, you will need to send a “#” or “D” (depending on the repeater controller) before every command sequence.***
- 3. Only one system can be used at a time, either Echolink or IRLP, not both. Echolink can support up to five simultaneous connections. IRLP can only support one connection at a time. IRLP utilizes conference server nodes to support simultaneous linking of multiple repeaters.***